

A B C D E  
Compal Confidential

Model Name : Bellemere\_BE  
Compal Project Name : B5W1E  
File Name : LA-D121P

# Compal Confidential

## B5W1E Schematics Document


AMD "Beema" Platform


AMD 15W APU With Puma+ Core

LA-D121P REV: 1.0

2015-04-16

| Compal Secret Data   |             |                 |            | Compal Electronics, Inc.      |                 |
|--|-------------|-----------------|------------|-------------------------------|-----------------|
| Security Classification  | Issued Date | Deciphered Date | 2016/03/27 | Title                         | Document Number |
| <small>THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF COMPAL ELECTRONICS, INC. WITHOUT THE WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.</small> |             |                 |            |                               |                 |
| Final  | Rev B       | B5W1E_LA-D121P  | 1.0        | Date: Tuesday, April 21, 2015 | Sheet 1 of 33   |





300-740 / SK 15-2 ale 2 A' can

| Vcc      | 3.3V        |        |        |        |             |
|----------|-------------|--------|--------|--------|-------------|
| Ra       | 100K +/- 1% |        |        |        |             |
| Board ID | Rb          | V min  | V typ  | V max  | EC AD       |
| 0        | 0           |        | 0.000V | 0.300V | 0x00 - 0x0B |
| 1        | 12K +/- 1%  | 0.347V | 0.354V | 0.360V | 0x0C - 0x1C |
| 2        | 15K +/- 1%  | 0.423V | 0.430V | 0.438V | 0x1D - 0x26 |
| 3        | 20K +/- 1%  | 0.541V | 0.550V | 0.559V | 0x27 - 0x30 |
| 4        | 27K +/- 1%  | 0.691V | 0.702V | 0.713V | 0x31 - 0x3B |
| 5        | 33K +/- 1%  | 0.807V | 0.819V | 0.831V | 0x3C - 0x46 |
| 6        | 43K +/- 1%  | 0.978V | 0.992V | 1.006V | 0x47 - 0x54 |
| 7        | 56K +/- 1%  | 1.169V | 1.185V | 1.200V | 0x55 - 0x64 |
| 8        | 75K +/- 1%  | 1.398V | 1.414V | 1.430V | 0x65 - 0x76 |
| 9        | 100K +/- 1% | 1.634V | 1.650V | 1.667V | 0x77 - 0x87 |
| 10       | 130K +/- 1% | 1.849V | 1.865V | 1.881V | 0x88 - 0x96 |
| 11       | 160K +/- 1% | 2.015V | 2.031V | 2.046V | 0x97 - 0xA3 |
| 12       | 200K +/- 1% | 2.185V | 2.200V | 2.215V | 0xA4 - 0xAD |
| 13       | 240K +/- 1% | 2.316V | 2.329V | 2.343V | 0xAE - 0xB7 |
| 14       | 270K +/- 1% | 2.395V | 2.408V | 2.421V | 0xB8 - 0xC0 |
| 15       | 330K +/- 1% | 2.521V | 2.533V | 2.544V | 0xC1 - 0xC9 |
| 16       | 430K +/- 1% | 2.667V | 2.677V | 2.687V | 0xCA - 0xD3 |
| 17       | 560K +/- 1% | 2.791V | 2.800V | 2.808V | 0xD4 - 0xDC |
| 18       | 750K +/- 1% | 2.905V | 2.912V | 2.919V | 0xDD - 0xE6 |
| 19       | NC          | 3.000V | 3.300V |        | 0xE7 - 0xFF |

## BOARD ID Table


| Board ID | PCB Revision |
|----------|--------------|
| 12       | EVT          |
| 13       | DVT          |
| 14*      | PVT          |
| 15       | Pre-MP       |
| 16       |              |
| 17       |              |
| 18       |              |
| 19       |              |

## SMBus List

| EC SMBus Port1 (+3VALW) |             |     | EC SMBus Port2 (+3VS) |             |     |
|-------------------------|-------------|-----|-----------------------|-------------|-----|
| Device                  | Address     | HEX | Device                | Address     | HEX |
| Smart Battery           | 0001 011X b | 16H | SB-TSI (APU)          | 1001 100X b | 98H |
|                         |             |     |                       |             |     |
|                         |             |     |                       |             |     |
|                         |             |     |                       |             |     |

### APU SMBus Port0 (+3VS) APU SMBus Port1(+3VALW)

| Device    | Address    | HEX | Device | Address | HEX |
|-----------|------------|-----|--------|---------|-----|
| DDR DIMM1 | 1010 000Xb | A0H |        |         |     |
| DDR DIMM2 | 1010 001Xb | A2H |        |         |     |
|           |            |     |        |         |     |
|           |            |     |        |         |     |




PCB B5W1E LA-D121P LS-D121P  
ZZZ  
  
HDMI\_ROYALTY  
ROYALTY HDMI W/LOGO+HDCP  
R0000003HM

## BOM Structure Table


| BOM Structure | BTO Item                       |
|---------------|--------------------------------|
| @             | Unpop                          |
| CONN@         | Connector part control by ME   |
| KBN@          | Stuff when use Kabini APU      |
| BMA@          | Stuff when use Beema APU       |
| CZL@          | Stuff when use CZ-L APU        |
| 233@          | Use for Audio Codec ALC233-VB2 |
| 255@          | Use for Audio Codec ALC255     |
| 283@          | Use for Audio Codec ALC283     |
| EMC@          | EMI pop component              |
| @EMC@         | EMI unpop component            |
| SP@           | Short pad for clear CMOS       |
| HDT@          | HDT+ for test phase, MP remove |
| RS@           | R-short                        |
| 45@           | HDMI royalty                   |
| 9012@         | Use KBC9012                    |
| 9022@         | Use KBC9022                    |
| BL@           | Keyboard backlight             |
| TPM@          | Use discrete TPM module        |
| ECI2C@        | Use EC I2C T/P                 |
| TPUSB@        | Use USB to I2C IC for T/P      |
| BYOC@         | Stuff when support BYOC        |
| NBYOC@        | Stuff when non-support BYOC    |
| JP@           | Jump                           |
| TP@           | Test point                     |


| STATE                | SIGNAL | SLP_S3# | SLP_S5# | +VALIN | +V  | +VS | Clock |
|----------------------|--------|---------|---------|--------|-----|-----|-------|
| Full ON              |        | HIGH    | HIGH    | ON     | ON  | ON  | ON    |
| S1(Power On Suspend) |        | HIGH    | HIGH    | ON     | ON  | ON  | LOW   |
| S3 (Suspend to RAM)  |        | LOW     | HIGH    | ON     | ON  | OFF | OFF   |
| S4 (Suspend to Disk) |        | LOW     | HIGH    | ON     | OFF | OFF | OFF   |
| S5 (Soft OFF)        |        | LOW     | LOW     | ON     | OFF | OFF | OFF   |


## APU POWER SEQUENCE





|  |                    |                 |            |                               |               |
|--|--------------------|-----------------|------------|-------------------------------|---------------|
| Re-Check   |                    |                 |            | Compal Electronics, Inc.      |               |
| Security Classification  | Compal Secret Data |                 |            |                               |               |
| Issued Date  | 2014/03/27         | Deciphered Date | 2016/03/27 | Title                         | NOTES LIST    |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF COMPAL ELECTRONICS, INC. WITHOUT THE WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. |                    |                 |            | Document Number               | Rev. 1.0      |
|  |                    |                 |            | B5W1E_LA-D121P                |               |
|  |                    |                 |            | Date: Tuesday, April 21, 2015 | Sheet 4 of 33 |

















| Security Classification  | Compaq Secret Data |            |      | Compaq Electronics, Inc.          |
|--|--------------------|------------|------|-----------------------------------|
| Issued Date  | Deciphered Date    | 2016/03/27 | Size | DDR3 SODIMM-I Socket              |
|  |                    |            | C    | Document Number<br>B5W1E_LA-D121P |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAQ ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. IT MAY NOT BE COPIED, REPRODUCED, OR DISCLOSED TO ANY THIRD PARTY WITHOUT THE PRIOR WRITTEN CONSENT OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAQ ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAQ ELECTRONICS, INC. |                    |            |      |                                   |
| Date: Thursday, April 16, 2015   | Page: 10 of 33     |            |      |                                   |




**DIMM B H:4mm STD**


|                         |                          |                 |            |                          |                       |       |
|-------------------------|--------------------------|-----------------|------------|--------------------------|-----------------------|-------|
| Security Classification | Compaq Secret Data       |                 |            | Compaq Electronics, Inc. |                       |       |
| Issued Date             | 2014/03/27               | Deciphered Date | 2016/03/27 | Title                    | DDR3 SODIMM-II Socket |       |
| Size                    | Document Number          |                 |            | Rev                      |                       |       |
| C                       | B5W1E_LA-D121P           |                 |            | 1.0                      |                       |       |
| Date:                   | Thursday, April 16, 2015 |                 |            | Sheet                    | 11                    | of 33 |


This sheet of engineering drawing is the proprietary property of Compaq Electronics, Inc. and contains confidential and trade secret information. This sheet may not be transferred from the custody of the competent division of R&D department of Compaq Electronics, Inc. without the written consent of Compaq Electronics, Inc. The information contained on this sheet may be used by or disclosed to any third party without prior written consent of Compaq Electronics, Inc.






| Security Classification   |            | Compal Secret Data |                |       | Compal Electronics, Inc. |           |                                |
|---|------------|--------------------|----------------|-------|--------------------------|-----------|--------------------------------|
| Issued Date   | 2014/03/27 | Deciphered Date    | 2016/03/27     | Title |                          | HDMI CONN |                                |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. |            |                    |                |       |                          |           |                                |
| Size  | B          | Document Number    | B5W1E_LA-D121P |       | Rev                      | 1.0       | Date: Thursday, April 16, 2015 |






| Security Classification   | Compaq Secret Data |                 |                | Compaq Electronics, Inc. |                   |  |
|---|--------------------|-----------------|----------------|--------------------------|-------------------|--|
| Issued Date   | 2013/10/28         | Deciphered Date | 2014/10/28     | Title                    | LAN_RTL8111GUS-CG |  |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAQ ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF RE20292 DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAQ ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAQ ELECTRONICS, INC. | Custom             | Document Number | B5W1E_LA-D121P | Rev 1.0                  |                   |  |

## HD Audio Codec





# Wireless LAN




| Security Classification   | Compal Secret Data             |                 |            | Compal Electronics, Inc. |  |         |
|---|--------------------------------|-----------------|------------|--------------------------|--|---------|
| Issued Date   | 2014/11/04                     | Deciphered Date | 2016/11/04 | Title                    |  |         |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. |                                |                 |            |                          |  |         |
|   | Size B                         | Document Number |            |                          |  |         |
|   |                                | B5W1E_LA-D121P  |            |                          |  | Rev 1.0 |
|   | Date: Thursday, April 16, 2015 | Sheet 17        | of 33      |                          |  |         |

## SATA HDD Conn.

## SATA ODD Conn.




change L51 from SM070003Y00 to SM070003K00




<8> USB3\_FRX\_DTX\_P0 R567 1 @EMC@ 0 0402\_5% USB3\_FRX\_L\_DTX\_P0  
<8> USB3\_FRX\_DTX\_N0 R563 1 @EMC@ 0 0402\_5% USB3\_FRX\_L\_DTX\_N0

<8> USB3\_FTX\_DRX\_P0 1 2 USB3\_FTX\_C\_DRX\_P0 R568 1 @EMC@ 0 0402\_5% USB3\_FTX\_L\_DRX\_P0  
<8> USB3\_FTX\_DRX\_N0 1 2 USB3\_FTX\_C\_DRX\_N0 R564 1 @EMC@ 0 0402\_5% USB3\_FTX\_L\_DRX\_N0


change L29 from SM070003Y00 to SM070003K00



## ON/OFF BTN



## USB & CR/B



### Security Classification

Issued Date

2014/03/27

### Compal Secret Data

Deciphered Date

2016/03/27

### Compal Electronics, Inc.

Title

USB2.0 / USB3.0

Size

Document Number

Rev

Custom

1.0

Sheet

19

of


33

THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC.



ACES\_51524-0140N-001 CONN@ R02 Nodify

Date: Thursday, April 16, 2015


KB Conn.



TP/TPM



Lid Switch  
(Hall Effect Switch)




Dual Amber+Blue

LED

LTST-S115TBKF-CA (SC50000C500)

Vf @ 5 mA :



UD5: 1.7 ~ 2.3V  
(3.3-1.7)/300=5.71 mA  
(3.3-2.3)/300=3.57 mA  
R min: 100 ohm  
R max 700 ohm

CB5: 2.65 ~ 3.05V  
(3.3-2.65)/50=13.00 mA  
(3.3-3.05)/100=5.0 mA  
R min: 50 ohm  
R max 475 ohm

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080

301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080

560 5% : SD028560080

200 5% : SD028200080

100 1% : SD034100080

150 1% : SD034150080


301 1% : SD034301080

680 1% : SD034680080

120 5% : SD028120080


560 5% : SD028560080

200 5% : SD028200080




| Security Classification   | Compal Secret Data |                 |            | Compal Electronics, Inc. |  |  |  |
|---|--------------------|-----------------|------------|--------------------------|--|--|--|
| Issued Date   | 2014/11/04         | Deciphered Date | 2016/11/04 | Title                    |  |  |  |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. |                    |                 |            |                          |  |  |  |
| Size: Custom Document Number: B5W1E_LA-D121P Rev: 1.0<br>Date: Thursday, April 16, 2015 Sheet: 21 of 33   |                    |                 |            |                          |  |  |  |

## FAN1 Conn




## FAN Conn


## Screw Hole




## KB BackLight Conn. Reserve



## Reset Circuit




## Reset Button




| Security Classification   | Compal Secret Data       |            |            | Title                    |
|---|--------------------------|------------|------------|--------------------------|
| Issued Date   | Deciphered Date          | 2016/11/04 | 2016/11/04 | Compal Electronics, Inc. |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPALELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTOMER OR THE COMPAL SECRET DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPALELECTRONICS, INC. WHETHER THE SHEET OR THE INFORMATION CONTAINED MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPALELECTRONICS, INC. |                          |            |            |                          |
| Size  | Document Number          |            |            |                          |
| Custom  | B5W1E_LA-D121P           |            |            | Rev 1.0                  |
| Date:   | Thursday, April 16, 2015 | Sheet      | 22         | of 33                    |


+5VALW TO +5VS  
+3VALW TO +3VS  
Load switch




*+1.8VALW TO +1.8VS  
+1.5V TO +1.5VS  
Load switch*





*+0.95VALW to +0.95VS*



|   |                          |                 |                |                          |                  |     |
|---|--------------------------|-----------------|----------------|--------------------------|------------------|-----|
| Security Classification   | Compal Secret Data       |                 |                | Compal Electronics, Inc. |                  |     |
| Issued Date   | 2014/03/27               | Deciphered Date | 2016/03/27     | Title                    | P22-DC INTERFACE |     |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. |                          |                 |                |                          |                  |     |
| Size  | B                        | Document Number | B5W1E_LA-D121P |                          | Rev              | 1.0 |
| Date:   | Thursday, April 16, 2015 |                 | Sheet          | 23                       | of               | 33  |




| Security Classification  |                          | Compal Secret Data |                | Compal Electronics, Inc. |      |
|--|--------------------------|--------------------|----------------|--------------------------|------|
| Issued Date  | 2014/10/20               | Deciphered Date    | 2016/10/20     | Title                    | DCIN |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPALELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPALELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPALELECTRONICS, INC. |                          |                    |                |                          |      |
| Page   | Custom                   | Document Number    | B5W1E_LA-XXXXP | Rev                      | 1.0  |
| Date:  | Thursday, April 16, 2015 | Sheet              | 24             | of                       | 33   |



| For KB9022 OTP | Active  | Recovery |
|----------------|---------|----------|
| VCIN0_PH(V)    | 92C, 1V | 56C, 2.V |
| PH202(ohm)     | 7.3K    | 26.11K   |


| For KB9012 sense 20mΩ | Active        | Recovery     |
|-----------------------|---------------|--------------|
| 45W                   | 48.15W, 0.73V | 38.7W, 0.59V |
| 65W                   | 69.55W, 0.73V | 55.9W, 0.59V |

PH202 under CPU bottom side :  
 CPU thermal protection at 92 degree C ( shutdown )  
 Recovery at 56 degree C +EC\_VCCA



2013/10/02  
 Add for ENE9022 Battery Voltage drop detection.  
 Connect to ENE9022 pin64 AD1.

Reserve for 2-cell design



For 45W adapter ==> action 48.15W , Recovery 38.7W

48.15W:  
 $I_{ada} = 0 \sim 2.253A$  ( $48.15W/19V = 2.534A$ )  
 $ADP\_I = 20 * I_{ada} * R_{sense}$   
 $ADP\_I = 20 * 2.534 * 0.02 = 1.01$   
38.7W:  
 $I_{ada} = 0 \sim 2.036A$  ( $38.7W/19V = 2.036A$ )  
 $ADP\_I = 20 * I_{ada} * R_{sense}$   
 $ADP\_I = 20 * 2.036 * 0.02 = 0.814$


$CP = 45W * 0.85 = 38.25W$


For 65W adapter ==> action 69.55W , Recovery 55.9W

69.55W:  
 $I_{ada} = 0 \sim 3.661A$  ( $69.55W/19V = 3.661A$ )  
 $ADP\_I = 20 * I_{ada} * R_{sense}$   
 $ADP\_I = 20 * 3.661 * 0.02 = 1.464$   
55.9W:  
 $I_{ada} = 0 \sim 2.942A$  ( $55.9W/19V = 2.942A$ )  
 $ADP\_I = 20 * I_{ada} * R_{sense}$   
 $ADP\_I = 20 * 2.942 * 0.02 = 1.177$

$CP = 65W * 0.85 = 55.25W$


| Security Classification   | Compal Secret Data |                 |            | Compal Electronics, Inc. |
|---|--------------------|-----------------|------------|--------------------------|
| Issued Date   | 2014/10/20         | Deciphered Date | 2016/10/20 | Title                    |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. |                    |                 |            |                          |
| Size  | Document Number    | Rev.            |            |                          |
| Custom  | B5W1E_LA-XXXXP     | 1.0             | Date:      | Thursday, April 16, 2015 |
|   |                    |                 | Sheet      | 25 of 33                 |






## Module model information


RT8207M\_V1.mdd For Single layer  
RT8207M\_V2.mdd For Dual layer




| Security Classification   | Compal Secret Data       |                 |            | Compal Electronics, Inc. |    |  |
|---|--------------------------|-----------------|------------|--------------------------|----|--|
| Issued Date   | 2014/10/20               | Deciphered Date | 2016/10/20 | Title<br>+1.5VP/+0.75VSP |    |  |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. |                          |                 |            |                          |    |  |
| Size  | Document Number          | Rev             |            |                          |    |  |
| Custom  | B5W1E_LA-XXXXP           | 1.0             |            |                          |    |  |
| Date:   | Thursday, April 16, 2015 | Sheet           | 28         | of                       | 33 |  |




|                |         |
|----------------|---------|
| VDDP_ALW_VCTRL | VDDPALW |
| 1              | 1.062V  |
| 0              | 0.96V   |




|   |                          |                 |            |                          |                    |     |
|---|--------------------------|-----------------|------------|--------------------------|--------------------|-----|
| Security Classification   | Compal Secret Data       |                 |            | Compal Electronics, Inc. |                    |     |
| Issued Date   | 2014/10/20               | Deciphered Date | 2016/10/20 | Via                      | +0.95VALW/+1.8VALW |     |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPERTY OF COMPAK ELECTRONICS, INC. AND CONTAINS COMPAK CONFIDENTIAL INFORMATION. THIS SHEET OF DRAWING IS NOT TO BE COPIED, REPRODUCED, OR DISCLOSED OUTSIDE OF THE COMPANY OR ITS SUBSIDIARIES, EXCEPT AS AUTHORIZED BY COMPAK ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAK ELECTRONICS, INC. |                          |                 |            |                          |                    |     |
| Rev   | Document Number          | B5W1E LA-XXXXP  |            |                          | Custom             | 1.0 |
| Date  | Thursday, April 16, 2015 | Sheet           | 29         | of                       | 33                 |     |



2013/10/16 Modify  
PQ801,PQ803 change to AON6552.  
PQ802,PQ804,PQ805 change to AON6554.



2013/10/22 Modify  
PH801,PH802 change to common part.



Delete PR834.PR835.PR836.PR839.PR840.PR841,  
follow vender FAE suggest.  
2013/11/29 modify.

1913, 11, 23 ~~modifying~~.

```

APU_core
TDC 20A
Peak Current 25A
OCP current > 32.5A
Load line -4mV/A
FSW=450kHz
DCR 1.4mohm +/-5%


```

```


APU_CORE_NB
TDC 13A
Peak Current 17 A
OCP current > 32.5A
Load line -4mV/A
FSW=450kHz
DCR 1.4mohm +/-5%
                                TYP          MAX
H/S Rds(on) : 6.7mohm , 8.5mohm
L/S Rds(on) : 3mohm , 3.8mohm

```


|   |                          |                 |                          |                 |          |
|---|--------------------------|-----------------|--------------------------|-----------------|----------|
| Security Classification   | Compal Secret Data       |                 | Compal Electronics, Inc. |                 |          |
| Issued Date   | 2012/06/19               | Deciphered Date | 2012/07/31               | Title           | CPU_CORE |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT OF COMPAL ELECTRONICS, INC. WITHOUT WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. THIS SHEET OF DRAWING CONTAINS INFORMATION WHICH IS THE TRADE SECRET OF COMPAL ELECTRONICS, INC. NO PART OF THIS SHEET OF DRAWING MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. | Size                     | Document Number |                          | Rev             | 1.0      |
| Custom  |                          |                 |                          | B5W1E LA-XXXXXP |          |
| Date:   | Thursday, April 16, 2015 | Sheet           | 30                       | of              | 33       |




+APU\_CORE (36.4)



+APU\_CORE\_NB (36.5)



+APU CORE



+APU CORE NB

### *Version change list (P.I.R. List)*

Page 1 of  
for PWR

| Security Classification   | Compal Secret Data                |                 |            | Compal Electronics, Inc. |          |      |
|---|-----------------------------------|-----------------|------------|--------------------------|----------|------|
| Issued Date   | 2014/10/20                        | Deciphered Date | 2016/10/20 | Title                    | PWR_PIR1 |      |
| THIS SHEET OF ENGINEERING DRAWING IS THE PROPRIETARY PROPERTY OF COMPAL ELECTRONICS, INC. AND CONTAINS CONFIDENTIAL AND TRADE SECRET INFORMATION. THIS SHEET MAY NOT BE TRANSFERRED FROM THE CUSTODY OF THE COMPETENT DIVISION OF R&D DEPARTMENT EXCEPT AS AUTHORIZED BY COMPAL ELECTRONICS, INC. NEITHER THIS SHEET NOR THE INFORMATION IT CONTAINS MAY BE USED BY OR DISCLOSED TO ANY THIRD PARTY WITHOUT PRIOR WRITTEN CONSENT OF COMPAL ELECTRONICS, INC. | Document Number<br>B5W1E_LA-XXXXP | Rev 1.0         |            |                          |          |      |
| Date: Thursday, April 16, 2015  | 1 Sheet                           | 32              | of         | 33                       | Custom   | 0828 |

| Item | Page     | Date       | Reason for change   | Phase |
|------|----------|------------|---|-------|
| 01   |          | 2015/02/05 | modify form A4W1E, i/o copy from Z5W1M  | DVT   |
| 02   | 11       | 2015/02/06 | update to DIMM*2  |       |
| 03   | 06       |            | del JHDT1 circuit   |       |
| 04   | 20       | 2015/02/09 | for TP diff device  |       |
| 05   | 18       |            | del EXT HDD connector   |       |
| 06   | 14       | 2015/02/11 | define 15" EVT  |       |
| 07   |          |            | Change all EMI/ESD BS to EMC@   |       |
| 08   | 15       | 2015/02/13 | del JP25 (confirm with EMI Eddie)   |       |
| 09   | 21       | 2015/02/24 | schematic update  |       |
| 10   | 07       |            | del Q2520 and change to 2505A   |       |
| 11   | 14       |            | APU_GPIO49 pull high change S0 domain, (+3VS)   |       |
| 12   | 15       |            | R1562/3949/3950 change to 1% tolerance  |       |
| 13   | 15       |            | replace R3959~3962 by RP10  |       |
|      |          |            | add R3935/R3936 for PH LAN_PME# & CLKREQ#   |       |
| 14   |          | 2015/02/25 | update power circuit.   |       |
| 15   | 14       |            | for common use Z5W1M I/O board  |       |
| 16   | 17       |            | schematic update  |       |
| 17   | 23       | 2015/02/26 | schematic update  |       |
| 18   | 17       |            | change R3956 to 0 ohm (@), and unpop R3955  |       |
| 19   | 08       |            | net swap D10 and 3/5V load switch for layout.   |       |
| 20   | 07       |            | R139/140 change to 0 ohm from R-S.  |       |
| 21   | 07       |            | C795 change to 5.6P (follow A4W1E)  |       |
| 22   | 18       | 2015/03/03 | schematic update  |       |
| 23   | 14       |            | Change R668 to PH +3VALW for Project define.  |       |
| 24   | 05       |            | Change R694/R695 to 1k ohm for Platform define  |       |
| 25   | 13,19,21 |            | JODD1 pin 16&17 not connect to GND  |       |
| 26   | 13       | 2015/03/04 | schematic update  |       |
| 27   | 15       |            | add dummy R3949/R3950 for CZL ID  |       |
| 28   | 19       |            | replace RP2 by R75~R77  |       |
| 29   | 5        | 2015/03/05 | swap L39/L41/L29/L49/L50/RP16/RP24 for layout   |       |
| 30   | 4        | 2015/03/06 | schematic update  |       |
| 31   | 23       | 2015/03/07 | swap RP1.3 & RP1.4  |       |
| 32   | 5        | 2015/03/10 | schematic update  |       |
| 33   | 15       | 2015/03/10 | swap Transformer T2507 pins   |       |
| 34   | 12       | 2015/03/13 | change L29,L51 from SM070003Y00 to SM070003K00  |       |
| 35   | 1,2      | 2015/03/18 | schematic update  |       |
| 36   | 13,15,19 | 2015/04/08 | add beem & kabini APU   |       |
| 37   |          | 2015/04/09 | Remove A4@, A6@, E1@, E2@   |       |
| 38   |          | 2015/04/09 | SWAP U3   |       |
| 39   |          | 2015/04/10 | add CZL-L APU   |       |
|      |          |            | Change L2004 to SH00000RT00   |       |
|      |          |            | Change JEDP1 pin define to follow Z5W1M   |       |
|      |          |            | Update Project Name & function block page   |       |
|      |          |            | remove co-layout footprint for DFB.   |       |
|      |          |            | Change R3923,R427,R428,R3858,R3925,R124,R125,R1682,R1690,R470,R471,R472,R3879,R1680,R563,R564,R567,R568,R467,R2631 to R-S |       |
|      |          |            | Update PCB PN to Ver.1.0 (DA6001FR010)  |       |

| Security Classification |                 | Compaq Secret Data |                 | Compaq Electronics, Inc.       |                 |
|-------------------------|-----------------|--------------------|-----------------|--------------------------------|-----------------|
| Issued Date             | Deciphered Date | Deciphered Date    | Deciphered Date | Title                          | HW-PIR          |
| 2014/03/27              |                 |                    | 2016/03/27      |                                |                 |
|                         |                 |                    |                 | Size                           | Document Number |
|                         |                 |                    |                 | C                              | B5W1E_LA-D121P  |
|                         |                 |                    |                 |                                | Rev. 1.0        |
|                         |                 |                    |                 | Date: Thursday, April 16, 2015 | Sheet 33 of 33  |